

FULLLOAD 1000

Datasheet

FULBAT™
BATTERY CHARGERS



SMART BATTERY CHARGER & MAINTAINER

SPECIFICATIONS

Voltage
6/12V

Stages
3

Current
1Ah

Battery
2>20 Ah

TECHNOLOGY COMPATIBILITIES

GEL

AGM

MF

DRY


WET

LiFePO4

CHARGING FEATURES

CHARGING FEATURES

FULLLOAD 1000 - 3 STAGES



Designed for lead-acid and lithium batteries, the all-new FULLLOAD 1000 is an automatic smart battery charger and maintainer for powersports batteries.

With 4 selectable modes including Lithium mode, the FULLLOAD 1000 is a 6V and 12V battery charger rated at 1A with battery capacity up to 20Ah. Safe and easy to use, the 3 steps of charge will ensure maximum performance and lifetime for all your batteries.

FEATURES

- Smart battery charger & maintainer
- For 6V-12V Lead Acid batteries (GEL, AGM, MF, DRY, Ca/Ca, WET) & 12V LiFePO4 batteries
- 1A charging current with battery capacity up to 20Ah (maintains all sizes)
- 4 charging modes
- Easy to set up and use
- Easy to read LED display
- Full protected against short circuit, wrong connections, overcharge and overheat
- Delivered with clamps and eyelet terminals set

BOX CONTENT

- Fulload 1000
- 1 clamps set
- 1 fused connection set

